

## BASIC SET UP

### Connect Power & Charge



1. Connect the speaker to a power source via the included AC cable.
2. While plugged into a power source, speaker will charge automatically.

**BEFORE FIRST USE:** Charge the unit for 6 hours. While charging, the RED LED indicator will flash slowly. When the unit is fully charged, the RED LED indicator will turn ON. When the battery is low, the RED LED indicator will flash rapidly.

### Manual Bluetooth Pairing



1. Press and hold BLUETOOTH button on the speaker until BLUE LED indicator starts flashing.
2. Make sure Bluetooth is activated on your device and is within 3 feet of the speaker.
3. Select the device "Monster GLO".
4. When paired, the BLUE LED indicator will stop flashing and remain steady.

### LED Light Panels



1. Press the LIGHT button to cycle LED brightness levels (0%, 25%, 50%, 75%, 100%)
2. Press COLOR/TIMER button to cycle colors modes (WHITE, CHROMA, GREEN, RED, DARK BLUE, YELLOW, LIGHT BLUE, PURPLE)
3. Press and hold the COLOR/TIMER button to change light timer (2H, 4H, 6H, 8H)

## EZ-PLAY TECHNOLOGY

### EZ-Play Multi-Speaker Connection



1. Press the button to turn on the first speaker, the Bluetooth LED and EZ-Play's Tx White LED will slow flash. Press and hold the key for 2 seconds and the White LED will begin to flash rapidly.




2. On additional EZPLAY speaker\*\*, press the key to turn on the second speaker, the Blue LED and EZ-Play's Tx White LED will flash slowly. Press and release the button and the EZ-Play's RX (Amber LED) will begin to flash slowly.




3. Press and hold the key for 2 seconds and the Amber LED will begin to flash rapidly.



4. Congratulations! You have successfully paired between the 2 speakers.



The White TX LED will solid on first speaker



The Amber RX LED will solid on second speaker

5. Repeat steps 1 - 3 to add additional speakers. You can connect up to 8 speakers total.

After connection is established, speakers automatically connect whenever powered ON and in range (<100 ft.). When a speaker is set to RECEIVE, AUX input and Bluetooth features are disabled. If a speaker is changed from its current mode (i.e., TRANSMIT to RECEIVE), it will have to be connected within Bluetooth pairing range (<10 ft.).

EZ-Play allows you to easily connect up to 8 speakers wirelessly and broadcast your favorite music to all speakers simultaneously to create an Audio Surround Experience indoors or outdoors.

\* EZ-Play technology also available on Monster Tower Of Music 1, Tower Of Music 2, and BTW 249.  
\*\* Additional EZ-Play speakers sold separately.