

BASIC SET UP

Connect Power & Charge



1. Connect the power cable to the Solara speaker.
2. Plug the power cable into a wall outlet.
3. **Flip the Power switch to ON**
4. Solara will enter Bluetooth Pairing mode automatically.
5. Pair with your Bluetooth device.

BEFORE FIRST USE: Charge the unit for **6 hours**. When fully charged the **RED LED +1, +2, +3** will stay solid. When low on battery the **RED LED** will flash rapidly. To Indicate battery level **Long Press (3 seconds)** the **Color/Battery Indicator** button.

Manual Bluetooth Pairing



1. Set the speaker source to Bluetooth (unpaired). **Blue LED will flash.**
2. Make sure the Bluetooth function is enabled on your device.
3. Place the Bluetooth device and speaker within pairing distance (~3 feet).
4. Press and hold the Bluetooth button for **3 seconds** to enter pairing mode (**BLUE LED will flash fast**).
5. Search for Bluetooth connections on your device. Select **"Monster Solara."**
6. The speaker will confirm connection with an audible message (**BLUE LED will turn solid**).

LED Light Panel



CHANGING COLORS
Short Press the Color/Battery Indicator button to cycle through the preset colors: **Chrome (Demo Mode), Red, Dark Blue, Green, Purple, Amber, Light Blue, White**

CHANGING LIGHT BRIGHTNESS/TIMER
Short Press the Light/Brightness button to cycle through the preset brightness level: **100%, 75%, 50%, 25%, OFF.**

NOTE: When light is OFF, press the key to turn light ON

Press and hold (3 seconds) the Light/Brightness button to adjust light timer duration: **2 Hours, 4 Hours, 6 Hours, 8 Hours**

EZ-PLAY TECHNOLOGY

EZ-PLAY Wireless Connection (Additional Speakers Sold Separately)



SET TX SPEAKER (TRANSMIT)

1. Make sure the speaker is powered on. The **Bluetooth BLUE LED** and **EZ-PLAY TRANSMIT (TX) WHITE LED** will flash slowly.
2. Press and hold the **EZ-PLAY** button for 3 seconds to put the speaker into Transmit Pairing Mode. The **TRANSMIT (TX) WHITE LED** will flash rapidly.
3. The **TX** speaker will automatically connect with **RX** speakers that are in Receive Pairing Mode and within pairing range (<10 ft).

SET RX SPEAKER (RECEIVING)

4. Make sure the speaker is powered on. The **Bluetooth BLUE LED** and **EZ-PLAY TRANSMIT (TX) WHITE LED** will flash slowly.
5. Press the **EZ-PLAY** button to change the speaker mode from Transmit to Receive. The **RECEIVE (RX) AMBER LED** will flash slowly.
6. Press and hold the **EZ-PLAY** button for 3 seconds to put the speaker into Receive Pairing Mode. The **RECEIVE (RX) AMBER LED** will flash rapidly.
7. The **RX** speaker will automatically connect with a **TX** speaker that is in Transmit Pairing Mode and within pairing range (<10 ft). **RECEIVE (RX) AMBER LED** will stay solid.
8. Repeat steps (4-8) to add up to **7 RX** speakers. Play audio through up to 8 speakers at once

DONT MISS OUT

EXCLUSIVE DEALS
FIRMWARE UPDATES
PRODUCTS RELEASES

SUBSCRIBE

<http://mymonsteraudio.com/>